

5

**METHOD AND APPARATUS FOR SENSING  
AND INTERPOLATING COLOR IMAGE DATA**

**Field**

10 This invention relates to a method and apparatus for sensing and interpolating image data, and more particularly, to an improved method and apparatus for efficiently and accurately sensing and interpolating color image data in an electronic imaging system.

**Background**

15 Electronic imaging cameras for recording still images are well known in the art. Such electronic imaging cameras may utilize two-dimensional electronic image sensing arrays such as charge-couple devices (CCD's) or complementary metal oxide semiconductor (CMOS) devices. Such two-dimensional image sensing devices  
20 typically comprise a regular array of image-sensing elements (*cf.*, pixels) that respond to incident illumination and provide an electronic signal corresponding to the intensity of this illumination. The electronic signals from the image sensing elements collectively form image data, which may be recorded in either analog or digital form. The signals may also, either immediately or subsequently, be displayed on viewing devices such as  
25 cathode-ray tubes or liquid crystal displays, or be printed to provide a hard copy.

The image sensing elements, on their own accord, discriminate primarily the intensity of the incident light, and not its color. In order to record a color image, it is common to cover each element with a color filter chosen from a small collection of filter colors.

Typical color imaging devices use one of two-color schemes. The first color scheme uses red, green and blue filters. The second color scheme uses cyan, magenta and yellow filters. In this way, each image-sensing element is made sensitive to the intensity of light having the color of its overlying filter. For example, an element covered by a red filter is responsive to red light, an element with a green filter to green light, and so on.

The disposition of the color filters on top of the array of sensing elements can be one of several well-known patterns. One such disposition is a repeating pattern of red, green and blue vertical stripes, so that all sensing elements within a single column respond to the intensity of a single color of light. Other dispositions include checkerboard arrays.

In such arrays, it is common practice to use a repeating pattern of colors. For example, one well-known and popular pattern of filters is known as the Bayer pattern. In the Bayer pattern, even numbered rows of the image-sensing device have alternating red and green filters, while odd numbered rows have alternating green and blue filters (the blue filters aligned with the green filters of the even numbered rows).

This method of collecting color image data, although widely used, suffers from the problem that each image sensing element records the intensity of only a single color. (*i.e.*, each image sensing element generates one-color image data) Image printing and display devices, on the other hand, commonly require information about the intensity of all of the colors at every pixel. The remedy to this problem is a process called "color recovery", in which the missing color intensities at each of the pixels are estimated from the data at surrounding pixels.

Conventionally, the missing color data is filled in by 2-dimensional interpolation. For example, when a Bayer pattern is used, each blue-sensing element is surrounded by four green-sensing elements, and the missing value of green at the blue-sensing element may be estimated as the average of the data from the four green-sensing neighbors.

Conventional color recovery methods can produce images with objectionable artifacts, such as "color fringes", near sharp edges. The usual approach to solving this problem eliminates color fringes at the expense of image sharpness either by blurring the picture or by suppressing selected spatial frequencies, known as anti-aliasing. Treating the image in either manner has the disadvantage of producing a blurred image.

A solution to the artifact problem is described by W.T. Freeman in U.S. Patent Nos. 4,663,655 and 4,774,565, both of which are herein incorporated. These patents set forth a color recovery scheme that uses nonlinear-filtering to produce an image that is sharp, correctly colored, and having a reduced incidence of the aforementioned artifacts.

In the Freeman patents, a color-recovery process and an apparatus for the implementation thereof are disclosed. The process could be applied either on 1-dimensional data, produced by a single-line array of sensing elements with color filters, such as in a flat-bed image scanner, or on 2-dimensional data, produced by a 2-dimensional array of sensing elements with color filters, such as in an electronic camera. The method is easiest to describe in the case of a 1 - dimensional linear array having a repeating pattern of red-, green- and blue-sensing elements *i.e.*, RGBRGB etc.

First, in accordance with said method, for each color pixel type (e.g., red), there will be one actually measured value for that color at every third sensing element, with values for that color missing at the two intervening pixels. The first step thus is to fill in the missing red (R) values at green (G) and blue (B) elements by using any of a number of well-known interpolation methods.

Secondly and similarly, the blue and green values are filled in for all pixels at which they have not been explicitly measured, using the same interpolation method.

Third, at this point red (R), green (G) and blue (B) values exist for every pixel. One of these values is an explicitly measured value, and the other two have been

obtained by interpolation. The interpolated values are denoted by attaching a prime, as in R' or G' or B'. The interpolated data now have the form:

| Element 1 | Element 2 | Element 3 | Element 4 | Element 5... |
|-----------|-----------|-----------|-----------|--------------|
| R, G', B' | R', G, B' | R', G', B | R, G', B' | R', G, B'    |

Fourth, at each pixel, the three color difference values, R-G, G-B, and B-R are calculated using either explicitly measured values or interpolated values such as they are available at each pixel.

Fifth, the R-G values across the row are then collected and subjected to a median filter of some predetermined length, typically an odd number in the range 5-11. The same is done with the G-B values and the B-R values, so that at each pixel there is a complete set of median-filtered color-difference values. These are denoted as (R-G)<sub>mf</sub>, (G-B)<sub>mf</sub> and (B-R)<sub>mf</sub>.

Sixth, at each pixel, the one explicitly measured color is combined with the two median-filtered color difference signals that contain that color to produce improved estimates for the previously interpolated color values. For the example array described above, the first pixel has an explicitly measured value for R, but interpolated values for G' and B'. In that case, the R values are combined with the median filtered color differences (R-G)<sub>mf</sub>, and (B-R)<sub>mf</sub> to find the final estimates:

$$G^{\wedge} = R - (R-G)_{mf}$$

$$B^{\wedge} = R + (B-R)_{mf}$$

where the ^ notation is used to denote a final recovered data value. This prescription is followed for each of the pixels, producing final color estimates that have the desirable properties claimed in the Freeman patents.

The Freeman method may be practiced on two-dimensional color data as well, using essentially the same prescription. In that case, for each sensing element,

calculations are performed on a symmetrically disposed neighborhood of elements. In steps 1 and 2, standard 2-dimensional interpolation methods, such as bi-cubic interpolation, are used to produce the initial guesses for the missing colors at the element.

5 Then, all of the color differences are found at each element, and in step 5, a 2-dimensional median filter is applied to the neighborhood of the element to find the median-filtered color difference values.

Finally, in step 6, improved estimates for the colors are calculated for colors that have not been explicitly measured at each pixel. This is done by combining the one color that has been measured with all of the median-filtered color-difference values that contain that color.

10 It should be appreciated that in each case, any missing color is finally determined by combining a measured color value with a single median-filtered color difference.

15 While the methods described in the Freeman patent provide desirable results in certain applications, when practiced on comparatively large two-dimensional color data arrays, the number of calculations needed for complete color recovery becomes correspondingly large. Since the speed of the methodology is tied to the number of its required calculation, there is an existing need for a method for recovering missing color data in a two-dimensional color data array that provides results comparable to those obtainable through the Freeman methodologies, yet not requiring as many calculations.

### Summary

25 In light of the above-mentioned need, the present invention provides a method (and apparatus) for recovering missing color data in a two-dimensional color array, said method (and apparatus) involving application of two one-dimensional non-linear interpolation processes.

In dealing with so-called real-time applications, it is sometimes found that the amount of computation involved in following known two-dimensional color recovery prescriptions becomes uneconomical to realize in special purpose circuitry, or too slow to implement as a computer program. By dividing the two-dimensional calculation into two one-dimensional calculations, fewer operations are required, yet good color fidelity is retained.

In a preferred mode of operation, the central steps of the operation are: First, for each row (or other first dimension) of the image, apply a one-dimensional color recovery prescription to recover all of the colors present in that row, and then for each column (or other second dimension) of the image apply another one-dimensional color recovery prescription to recover, at each element, any colors that were not already determined. The method, in greater detail, can be defined as electronically capturing and processing image information by: (a) providing a two dimensional array of discrete image sensing elements, each discrete element capable of providing an electronic information signal in response to incident illumination, said electronic information signal corresponding to the intensity of said incident illumination, each discrete element being specifically responsive to one of at least three predetermined colors; (b) obtaining first color image data by exposing the two dimensional array to image information bearing illumination such that each discrete element provides said electronic information signal, said first color image data comprising the collection of said electronic information signals; (c) recovering missing color information along a first dimension by (i) interpolating the first color image data along said first dimension to provide first interpolated color data for each of the discrete elements, (ii) forming a first difference channel between said first color image data and said first interpolated color data, and (iii) applying a first one-dimensional non-linear filter to said first difference channel, whereby a second color image data is obtained for each of the discrete elements; and (d) recovering missing color information along a second dimension by (i) interpolating the second color image data along said second dimension to provide second interpolated color data for each of the discrete elements, (ii) forming

a second difference channel between said second color image data and said second interpolated color data, and (iii) applying a second one-dimensional non-linear filter to said second difference channel, whereby a third color image data is obtained for each of the discrete elements.

5 In light of the above, it is a principal object of the present invention to provide a method for recovering missing color data in a two-dimensional color data array.

It is another object of the present invention to provide a method for recovering color data in a two-dimensional color data array, the method being comparatively quick in its operation, yet providing good accuracy in respect of resultant color fidelity.

It is another object of the present invention to provide a method for recovering color image data in a two-dimensional color data array, the method involving the conduct of two one-dimensional non-linear interpolations.

It is another object of the present invention to provide an apparatus well-suited for conducting two one-dimensional non-linear interpolations for the purpose of recovering image color data in a two-dimensional color data array.

These and other objects of the present invention will become apparent from the following detailed description of presently preferred embodiments of the invention, taken in conjunction with the accompanying drawings.

### Brief Description of the Drawings

Fig. 1 is a schematic block diagram of an apparatus for sensing and interpolating color image data (as in electronic imaging system) according to an embodiment of the present invention.

Fig. 2 is a detailed schematic block diagram of the first color recovery filter 114 from Fig. 1.

Fig. 3 is a detailed schematic block diagram of a variant of the second color recovery filter 122 shown in Fig. 1, said variant being configured particularly for a so-called "3-color" electronic imaging system.

Fig. 4 is a detailed schematic block diagram of another variant of the second color recovery filter 122 shown in Fig. 1, said variant being configured particularly for a so-called "3-color" electronic imaging system.

Fig. 5 is a detailed schematic block diagram of a variant of the second color recovery filter 122 shown in Fig. 1, said variant being configured particularly for a so-called "4-color" electronic imaging system.

Fig. 6 is a more detailed block diagram of another variant of the second color recovery filter 122 shown in Fig. 1, said variant being configured particularly for a so-called "4-color" electronic imaging system.

Figs. 7 and 8 are examples of configurations of discrete image sensing elements 20 employed in accordance with certain embodiments of the present invention.

### Detailed Description

Conventionally, the recovery of non-sampled image data missing from the sampled one-color, or "first color", image data received from an electronic two-dimensional array of image sensing elements requires 2-dimensional processing in the region about each sensing element. The present invention can accomplish similar results -- in respect particularly of certain array configurations (*e.g.*, "Bayer"-type configurations) -- with fewer calculations, by essentially "decoupling" the conventional 2-dimensional process into two-incremental 1-dimensional processes. The first 1-dimensional color recovery process generates intermediate second color image data from the sampled first color image data. The second 1-dimensional color recovery process generates the final and desired third color image data from the second color image data.

The variety of electronic image sensing arrays, for which application of the present invention is envisaged, is broad. Regardless, all will typically comprise a



two-dimensional array of discrete image sensing elements, wherein each discrete element is capable of providing an electronic information signal corresponding to the intensity of any illumination incident thereon, and wherein each discrete element is specifically responsive to one of at least three predetermined colors.

5           As used herein, "color" shall mean a range of wavelengths within the electromagnetic spectrum that includes not only visible light, but the infrared and ultraviolet regions as well. The most common predetermined colors are either red, green, and blue, or cyan (a combination of the green and blue wavelengths), magenta (a combination of the red and blue wavelengths), and yellow (a combination of the red and green wavelengths). The color sensitivity of the image sensing elements is typically accomplished by filtering input illumination so that different image sensing elements receive colored illumination.

10           By exposing the two-dimensional array to image-information bearing illumination, a collection of each electronic information signal received from each discrete element is obtained. This collection of signals forms the raw unprocessed one-color image data from which fully-recovered third color image data can be derived.

15           The first step towards deriving the fully-recovered third color image data is to first recover missing color information along a first dimension (e.g., along rows of the array). This is accomplished by interpolating the first color image data along the first dimension to provide a first-interpolated color data for each of the discrete elements, then forming a difference channel between the first color image data and the first-interpolated color data, and then applying a one-dimensional non-linear filter on the difference channel and combining with the first color data to obtain so-called first-recovered image data. The second color image data comprises a combination of the first-recovered image data and the first color image data.

20           The second step derives fully-recovered third color image data from the two color image data by recovering missing color information along a second dimension (e.g., along columns of the array). More particularly, the second color image data is obtained by interpolating along the second dimension to provide second-interpolated

data for each of the discrete elements, then forming a difference channel between the second color image data and the second-interpolated data, and then applying a one-dimensional non-linear filter on the difference channel and combining with the second color data to obtain the so-called second-recovered image data. The third color image data comprises a combination of the second-recovered image data and the second color image data.

As used herein, the term "difference channel" shall not be restricted to a channel containing a single color difference signal, but may include multiple color differences. For example, a single difference channel may contain both (red-blue) and (red-green) color difference signals. Likewise, terms such as "first-interpolated data" and "second color data" shall be used to refer to data containing multiple color signals.

In general, an apparatus useful for implementing the inventive methodology will comprise (a) a two-dimensional array of discrete image sensing elements, (b) a first color recovery module, and (c) a second color recovery module.

The two-dimensional array includes charge coupled devices (CCDs), complementary-metal-oxide-semiconductor (CMOS) devices, and other known 2-dimensional sensor arrays in which individual sensing elements produce an output signal that is responsive to the intensity of the illumination incident on the image sensing element.

The discrete image sensing elements may be arranged in any predetermined pattern. The individual elements receive light reflected from an object and imaged through an optical system and, in response thereto, provides an electronic signal proportional to the intensity of the incident illumination. In one embodiment, the individual image sensing elements are arranged in a rectangular grid pattern, such that they form a plurality of rows and columns. Other arrangements are anticipated. For example, as shown in FIG. 8 and discussed in Example 3, arranging the image sensing elements according to a hexagonal grid pattern will result in a plurality of rows and columns in which the rows and columns are not perpendicular. (See, first and second dimensions 10 and 12 in FIG. 8).

The most preferred arrangement for the discrete image sensing elements involves use of alternating rows of red-green and green-blue filters that form a three-color checkerboard pattern known within the art as the "Bayer pattern". An example of a Bayer pattern is shown FIG. 7. As shown therein, one will appreciate that (a) no two contiguous discrete elements 20 that are along the first or second dimension 10, 12 are specifically responsive to same color, and (b) no more than one discrete element is positioned contiguously between two discrete elements that are specifically responsive to the same color along the first and second dimensions 10, 12.

As mentioned hereinabove, each discrete element is capable of providing an electronic information signal corresponding to the intensity of any illumination incident thereon, and wherein each discrete element is specifically responsive to one of at least three predetermined colors. When the array is exposed, the collection of signals received from each element is digitized and provided as first color image data.

The first and second color recovery modules operate in predetermined separate dimensions of the first color image data to perform the two 1-dimensional color recovery operations. For example, as explained in more detail below, if the individual image sensing elements are arranged in rows and columns, one of the color recovery modules may operate in a first dimension corresponding to the rows of data and the other color recovery module may operate in a second dimension corresponding to the columns of data.

The first of the color recovery modules includes a first interpolator configured and arranged to interpolate in the first dimension the one-color image data received from the image-sensing array. The first interpolator provides output data that includes a plurality of first interpolated color data that corresponds to each individual image sensor element. Each of the first plurality of interpolated color data that corresponds to an individual image sensor element will be of a different sampled color than the first color data directly sampled by the individual image sensor element.

The plurality of first color data and the plurality of first interpolated color data are combined and filtered in the first dimension to constitute a first-recovered

color data corresponding to each individual image sensor element. The output of the first color recovery operation is a plurality of second color data that includes the first color data and the first-recovered color data corresponding to each individual image sensor element. As used herein, first-recovered data refers to color data corresponding to each individual image sensor element that will be of a different color than that the first color data sampled directly by that particular image sensor element. For example, if an individual image sensor element provides first color data on red light incident thereon, the first-recovered color data could be green, blue or other predetermined colors other than the directly measured red color.

The second of two 1-dimensional operations is accomplished by the second color recovery module, which includes a second interpolator configured and arranged to interpolate, along a different dimension, the plurality of second color data received from the first color recovery module. The second interpolator provides output data that includes a plurality of second interpolated data corresponding to each individual image sensor element.

The plurality of second interpolated data and the plurality of second color data are combined and filtered in the second dimension to produce second-recovered color data associated with each image sensor element. As used herein, second-recovered data refers to a color data corresponding to each individual image sensor element that will be of different color than the first color data provided by the individual image sensor element and the first-recovered data described above. The output of the second color recovery operation is a plurality of third color data that includes the second color data and the second-recovered color data corresponding to each individual image sensor element.

Although the present invention allows broad variation, to more tangibly illustrate its scope, particular embodiments and apparatuses for the implementation of the inventive methodology, and components thereof, are set forth in FIGS. 1 to 8.

Figure 1 is a block diagram of color recovery apparatus 100 for recovering three colors of data. Color recovery apparatus 100 includes an electronic

imaging system (not shown) providing a plurality of first color data 112 as an input to a first color recovery module 114. The first color recovery module 114 operates on first color data 112 in the first dimension and provides an output of a plurality of second color data 128, comprised of the first color data and first-recovered color data. Second color recovery module 122 receives as an input the second color data 128 and provides as an output a plurality of third color data 132.

First color data 112 is a schematic representation of the plurality of first color data. As described above, each of the first color data 112 corresponds to one of the individual image sensor elements in the image sensor array.

In the first illustrative embodiment shown in Figure 1, data R 109 represents a value of red filtered light measured at a particular individual image sensor element, data G 111 represents a value of green filtered light measured at a particular individual image sensor element, and data B 115 represents a value of blue filtered light at a particular individual image sensor element. In the first embodiment, the first dimension of the first color data 112 corresponds to the rows of the plurality of individual image sensor elements. Similarly, the second dimension of the first color data 112 corresponds to the columns of the plurality of the individual image sensor elements.

First color recovery module 114 includes first interpolator 116 and first color recovery filter 118. First interpolator 116 receives the plurality of first color data 112 and interpolates this data in the first dimension to produce a first-interpolated color data 120. The (') notation indicates an interpolated color value.

First-interpolated color data 120 and first color data 112 are filtered and combined in the first dimension by color recovery filter 118 to fully recover a second color data 128 for each individual image sensor element in the image sensor array, where the (^) notation indicates a recovered color data.

Second color data 128 is provided to second interpolator 124 that interpolates the second color data 128 in the second dimension to provide second-interpolated color data 130.

Second-interpolated color data 130 and second color data 128 are filtered and combined in the second dimension by second color recovery filter 126 to fully recover a third color data 132 for each individual image sensor element in image sensor array.

5 Figure 2 illustrates a more detailed description of the first recovery system 114 of the first embodiment of the color recovery system. In Fig. 2, G1 represents green color data contained in the rows of data containing red color data and G2 represents green color data contained in the rows of data containing blue color data.

Two pairs of interpolators are used, one pair for the rows containing R and G1 data, and one pair for the rows containing the B and G2 data. The interpolator may be any conventional interpolator, i.e. linear, spline, sinc, or other types as well. The individual choice of a particular type of interpolator is considered to be within the skill of the art.

10 Interpolators 202 and 216 receive R data 218 and G1 data 220 respectively and provide interpolated data via lines 205 and 215 respectively. In this embodiment, the R and G1 data alternate, and switch 204 is used to select and to couple the interpolated data on lines 205 and 215 to combiner 210 via line 209. Switch 206 couples either R 218 or G1 220 first color data to combiner 210. Switch 206 selects the other color from that of switch 204. In this embodiment, combiner 210 forms a difference data wherein the difference between R and G1 data corresponding to the same individual image sensor element is provided according to:

- 15 (1)  $R - G1'$ , or  
(2)  $R' - G1$ .

This difference is provided via difference channel 211 to filter 212.

25 Filter 212 is a non-linear filter that is provided to remove narrow peaks and valleys within the color-difference data. A particular class of non-linear filters capable of this type of response is rank-order filters, and in the preferred embodiment, a median rank-order filter is used. A suitable median filter is described in the U.S. Patent 4,802,108 assigned to Polaroid Corporation, which is herein incorporated by

reference. Combiner 214 combines the first color data selected by switch 206 with the filtered difference data 213. The combiner 214 provides:

$$(3) \quad R - F(R - G1), \text{ or}$$

$$(4) \quad G1 + F(R - G1).$$

5  $F()$  represents the operation of filter 212. As can be seen from equations (3) and (4), the recovered green data  $G1^{\wedge}$  are provided by equation (3) and recovered red data  $R^{\wedge}$  are provided by equation (4). These recovered color data are provided via line 217.

Similarly, interpolators 222 and 236 receive B data 238 and G2 data 240 respectively and provide interpolated data via lines 225 and 235 respectively. In this illustrated embodiment, the B and G2 data alternate, and switch 224 is used to select and to couple the interpolated data on lines 225 and 235 to combiner 230 via line 229.

Switch 226 couples either B 238 or G2 240 first color data to combiner 230. Switch 226 selects the other color from that of switch 224. The combiner 230 forms a difference data wherein the difference between B and G2 data corresponding to the same individual image sensor element is provided according to:

$$(5) \quad B - G2', \text{ or}$$

$$(6) \quad B' - G2.$$

This difference is provided via difference channel 231 to filter 232.

20 Filter 232 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference signal. As previously discussed, a median rank-order filter is used. Combiner 234 combines the first color data selected by switch 226 with the filtered difference data 233. Also, combiner 234 provides:

$$(7) \quad B - F(B - G2), \text{ or}$$

$$(8) \quad G2 + F(B - G2).$$

25 Where  $F()$  represents the operation of filter 232. As can be seen from equations (7) and (8), the recovered green data  $G2^{\wedge}$  are provided by equation (7) and the recovered blue data  $B^{\wedge}$  are provided by equation (8). These recovered color data are provided via line 237.

The description of module 114 applies both to a 3-color and to a 4-color system. In a 3-color system, G1 and G2 refer to the same physical color, whereas they will represent separate and distinct physical colors in a 4-color system.

Figure 3 is a block diagram providing further detail for the second color recovery module 122 of the first embodiment of Fig. 1. This diagram applies specifically to recovery of colors within the odd numbered columns of the image for a 3-color system.

Interpolator 302 receives R data 301 that consists of first color data and interpolates this data in the second dimension to provide red data corresponding to every individual image sensor element. Similarly interpolator 314 receives B data 303 that consists of first-recovered color data and interpolates this data in the second dimension to provide blue data corresponding to every individual image sensor element. As above, switch 306 selects interpolated or first-recovered blue data to provide as inputs to combiner 308, and switch 304 selects interpolated or first color red data to provide as inputs to combiners 308, 312 and 322. In this embodiment, first combiner 308 forms the difference between the blue and red data corresponding to each individual image sensor element according to:

$$(9) \quad R-B', \text{ or}$$

$$(10) \quad R'-B^{\wedge}.$$

This difference is provided via difference channel 309 to filter 310.

Filter 310 can be a non-linear filter, such as those previously identified, that is provided to remove narrow peaks and valleys within the color difference signal 309. Combiner 312 combines the red data selected by switch 304 with the filtered difference data 311. In this case, second combiner 312 provides:

$$(11) \quad R-F(R-B), \text{ or}$$

$$(12) \quad R'-F(R-B).$$

F() represents the operation of filter 310. Equations (11) and (12) illustrate that the second-recovered blue data  $B^{\wedge}$  are provided by equation (11). The



data provided by equation (12) are not used. These recovered color data are provided via line 317 to selector switch 328.

A third combiner 322 combines the red data selected by switch 304 with green data 321. The green data may be either first color or first-recovered color data, depending on whether the image sensor element for which the computation is being made is an even numbered element or an odd numbered element in the second dimension of the image sensor. In either case, this data will be denoted simply as G. The third combiner 322 forms the difference between the red and green data corresponding to each individual image sensor element according to:

$$(13) \quad R-G, \text{ or}$$

$$(14) \quad R'-G.$$

This difference is provided via difference channel 323 to filter 324.

Filter 324 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference signal 323 and is also similar to those previously identified. Fourth combiner 326 combines the green data 321 with the filtered difference data 325. In one embodiment the fourth combiner 326 provides:

$$(15) \quad G+F(R-G), \text{ or}$$

$$(16) \quad G+F(R-G).$$

In this case, F() represents the operation of filter 324. As can be seen from equations (15) and (16), the second-recovered red data  $R^{\wedge}$  are provided by equation (16). The data provided by equation (15) are not used. These recovered color data are provided via line 327 to a third selector switch 328.

As described above, this apparatus provides second-recovered blue data via line 317 for odd numbered elements in the second dimension of the image sensor, and it provides second-recovered red data via line 327 for even numbered elements in the second dimension of the image sensor. Selector switch 328, operating in synchrony with switches 304 and 306, transfers these recovered color data to line 329.

The second color module 122 has been described above according to its operation for odd numbered columns along the second dimension of the image data.

The same apparatus can be used to perform the second color recovery for even numbered columns along the second dimension of the image data. The description of the apparatus is changed only in that the red input data R 301 and the blue input data B 303 are interchanged, and the three synchronous switches 304, 306 and 328 are initialized to positions opposite to those shown in Figure 3. In this configuration, the second-recovered color data on line 317 is red data, and the second-recovered color data on line 327 is blue data.

The first and second color recovery modules illustrated in Fig. 2 and Fig. 3 always generate recovered color values by using a combination of an explicitly measured color value with a filtered color difference. This prescription yields the best accuracy for the recovered color values. However, by relaxing this constraint and incurring a small penalty in color fidelity, we can substantially reduce the computational requirements of the second color recovery module.

In this form of the color recovery method, which we shall refer to as the "abbreviated procedure", any missing colors recovered in the horizontal row operation are treated, in subsequent steps, as though they had been measured explicitly. The consequence of this change is that fewer filtered color-differences are needed in the vertical column operations, and therefore fewer of the computationally intensive filtering operations are needed.

Fig. 4 illustrates another version of the second color recovery module 122 in which the abbreviated procedure is implemented for color recovery in a three-color system. Interpolator 402 receives R data 401 that consists of both first and first-recovered color data and interpolates this data in the second dimension to provide second-interpolated red data corresponding to every individual image sensor element. Similarly, interpolator 414 receives B data 403 that consists of both first and first-recovered color data and interpolates this data in the second dimension to provide second-interpolated blue data corresponding to every individual image sensor element. Switch 404 selects different second-interpolated colors to provide as input to combiner 408, and switch 406 selects different first color data or first-recovered color data to

provide as input to combiner 408 and combiner 412. In this case, combiner 408 forms the difference between the blue and red data corresponding to each individual image sensor element according to:

$$(17) \quad R-B', \text{ or}$$

$$(18) \quad R'-B.$$

The values of R and B (unprimed) may be either first or first-recovered color data. The difference is provided via difference channel 409 to filter 410.

Filter 410 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference signal 409 and it is preferred to be a median rank-order filter as previously discussed. Second combiner 412 combines the second color data selected by switch 406 with the filtered difference data 411.

Combiner 412 in this embodiment provides:

$$(19) \quad B+F(R-B), \text{ or}$$

$$(20) \quad R-F(R-B)$$

where  $F()$  represents the operation of filter 410. As can be seen from equations (19) and (20), the second-recovered red data  $R^{\wedge}$  are provided by equation (19) and the second-recovered blue data  $B^{\wedge}$  are provided by equation (20). These recovered color data are provided via line 415.

The above apparatus may also be modified to recover four colors per individual image sensor element. In the four color recovery system, the first color recovery module shown in Fig. 2, which recovers a second non-sampled color corresponding to each individual image sensor element, can be the same. However, the structures and apparatus of the second color recovery module must be more complex in order to recover the remaining two non-sampled colors corresponding to each individual image sensor element.

The color data denoted as G1 and G2 are now understood to correspond to two different colors. For purposes of illustration, these colors will be described as two distinct shades of green, but they may be any two colors and this description should not be construed as limiting the scope of the invention in any way.

Figure 5 illustrates a second color recovery module designed for the odd columns in a four-color recovery system. In the embodiment illustrated in Fig. 5, G1 represents green color data contained in the rows of data containing red color data (odd rows) and G2 represents green color data contained in the rows of data containing blue color data (even rows).

In the illustrated embodiment of Fig. 5, four (in two pairs) interpolators are used. The interpolation for each color is conducted in the second dimension, which in the illustrated embodiment is vertically along the columns. For each color either the first color data or the first-recovered color data is used in the interpolation.

One interpolator will interpolate the B data, one interpolator will interpolate the R data, one interpolator will interpolate the G2 data, and one interpolator will interpolate the G1 data. Thus, all data associated with an individual image sensor element will now have four colors, a first color data, a first-recovered color data, and two second-interpolated color data. The interpolators may be any conventional interpolator known in the art.

Interpolators 502 and 518 receive B data 514 and R data 516 respectively, and provide second-interpolated data via lines 503 and 519 respectively.

Switches 504 and 520 are used to select and to couple the data to combiner 506. The switches couple first color red data 516 and second-interpolated recovered blue data 503, or else first-recovered blue data 514 and interpolated red data 519, based on whether an odd row or an even row of data is being combined.

If an odd row is being combined, then R 516 data and interpolated values of B<sup>^</sup> 503 are used. If an even row is being combined B<sup>^</sup> 514 data and interpolated values of R 519 are used. Combiner 506 forms a difference data wherein the difference between R and B data corresponding to the same individual image sensor element is provided according to:

$$(21) \quad R-B^{\wedge}, \text{ or}$$

$$(22) \quad R^{\wedge}-B.$$

This difference is provided via difference channel 507 to filter 508.

Filter 508 is a non-linear filter of the previous types disclosed. Combiner 510 combines the red data selected by switch 520 with the filtered difference data. In this case, combiner 510 provides:

(23)  $R - F(R - B)$ , or

(24)  $R' - F(R - B)$ .

$F()$  represents the operation of filter 508. As can be seen from equations (23) and (24), the second-recovered blue data are provided by equation (23). The data provided by equation (24) will not be used.

Similarly, interpolators 524 and 540 receive  $G2$  data 536 and  $G1^\wedge$  data 538 respectively, and provide interpolated data via lines 525 and 541 respectively. Switches 526 and 542 are used to select and to couple the data to combiner 528. The switches couple interpolated  $G2$  data 536 and first-recovered  $G1^\wedge$  data 538, or else measured  $G2$  data 536 and second-interpolated recovered  $G1^\wedge$  data 541, based on whether an odd row or an even row of data is being combined.

If an odd row is being combined, then second-interpolated values of  $G2$  525 and first-recovered values of  $G1^\wedge$  538 are used. If an even row is being combined then first color values of  $G2$  536 and second-interpolated recovered values of  $G1^\wedge$  541 are used.

The combiner 528 forms a difference data wherein the difference between  $G2$  and  $G1$  data corresponding to the same individual image sensor element is provided according to:

(25)  $G2' - G1^\wedge$ , or

(26)  $G2 - G1^\wedge$ .

This difference is provided via difference channel 529 to filter 530.

As previously discussed, filter 530 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference data. Combiner 532 combines the color data selected by switch 526 with the filtered difference data. In one embodiment combiner 532 provides:

$$(27) \quad G2'-F(G2-G1), \text{ or}$$

$$(28) \quad G2-F(G2-G1),$$

where  $F()$  represents the operation of filter 530. As can be seen from equations (27) and (28), the second-recovered green data  $G1^{\wedge}$  are provided by equation (28). The data provided by equation (27) are not used.

A third combiner 544 receives red data selected by switch 520 and  $G2$  data selected by switch 526. These switches couple first color  $R$  data 516 and second-interpolated  $G2$  data 525, or else first color  $G2$  data 536 and second-interpolated  $R$  data 519, based on whether an odd row or an even row of data is being combined.

If an odd row is being combined then measured values of  $R$  516 and interpolated values of  $G2$  525 are used. If an even row is being combined then interpolated values of  $R$  519 and measured values of  $G2$  536 are used.

Combiner 544 forms a difference data wherein the difference between  $R$  and  $G1$  data corresponding to the same individual image sensor element is provided according to:

$$(29) \quad R-G2', \text{ or}$$

$$(30) \quad R'-G2.$$

The difference is provided on difference channel 545 to filter 546.

Filter 546 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference data. The filtered difference data produced by filter 546 is provided on line 547.

Combiner 548 combines the color data selected by switch 520 with the filtered difference data 547. In one embodiment combiner 548 provides:

$$(31) \quad R-F(R-G2), \text{ or}$$

$$(32) \quad R'-F(R-G2).$$

In this case,  $F()$  represents the operation of filter 546. As can be seen from equations (31) and (32), the second-recovered green data  $G2^{\wedge}$  are provided by equation (31). The data provide by equation (32) are not used.

Combiner 550 combines the color data selected by switch 526 with the filtered difference data 547. In one embodiment combiner 550 provides:

$$(33) \quad G2' + F(R - G2), \text{ or}$$

$$(34) \quad G2 + F(R - G2).$$

5  $F()$  represents the operation of filter 546 in these equations. The second-recovered red data  $R^{\wedge}$  are provided by equation (34) and the data provided by equation (33) are not used.

The second color recovery module 122 has been described above according to its operation for odd numbered columns along the second dimension of the image data. The same apparatus can be used to perform the second color recovery for even numbered columns along the second dimension of the image data. The description of the apparatus is changed only in that: 1) the blue input data 514 and the G2 input data 536 are interchanged, and 2) the red input data 516 and the G1 input data 538 are interchanged. In this configuration, the second-recovered color data on line 511 are  $G2^{\wedge}$  data, the second-recovered color data on line 533 are  $R^{\wedge}$  data, the second-recovered color data on line 549 are  $B^{\wedge}$  data, and the second-recovered color data on line 551 are  $G1^{\wedge}$  data.

Another version of the second color recovery module 122 operates as illustrated in Fig. 6. This version illustrates the abbreviated procedure for the second color recovery in a 4-color system. The same figure applies to both odd and even numbered columns. Interpolator 602 receives second color R data 618 and interpolates this data in the second dimension to provide second-interpolated red data.

Similarly, interpolator 616 receives second color G2 data 620 and interpolates this data in the second dimension to provide second-interpolated G2 data.

25 Switch 604 and switch 606 select different colors to provide as inputs to combiner 610. In this situation, combiner 610 forms the difference between the R and G2 data corresponding to each individual image sensor element according to:

$$(35) \quad R - G2', \text{ or}$$

$$(36) \quad R' - G2.$$

The difference is provided via difference channel 611 to filter 612.

Filter 612 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference signal 611. Combiner 614 combines the second color data selected by switch 606 with the filtered difference data 613. In this embodiment combiner 614 provides:

$$(37) \quad R-F(R-G2), \text{ or}$$

$$(38) \quad G2+F(R-G2)$$

where  $F()$  represents the operation of filter 612. As can be seen from equations (37) and (38), the second-recovered  $G2$  data  $G2^{\wedge}$  are provided by equation (37) and the second-recovered red data  $R^{\wedge}$  are provided by equation (20). These recovered color data are provided via line 617.

Interpolator 622 receives second color B data 638 color data and interpolates this data in the second dimension to provide second-interpolated B data.

Similarly, interpolator 636 receives second color G1 data 640 and interpolates this data in the second dimension to provide second-interpolated G1 data.

Switch 624 and switch 626 select different colors to provide as inputs to combiner 630. Combiner 630 forms the difference between the B and G1 data corresponding to each individual image sensor element according to:

$$(39) \quad G1-B', \text{ or}$$

$$(40) \quad G1'-B.$$

The difference is provided via difference channel 631 to filter 632.

In this case, filter 632 can be a non-linear filter that is provided to remove narrow peaks and valleys within the color difference signal 631 and combiner 634 combines the second color data selected by switch 626 with the filtered difference data 633. In one embodiment combiner 634 provides:

$$(41) \quad G1-F(G1-B), \text{ or}$$

$$(42) \quad B+F(G1-B),$$

where  $F()$  represents the operation of filter 632. As can be seen from equations (41) and (42), the second-recovered B data  $B^{\wedge}$  are provided by equation (41) and the second



recovered G1 data  $G1^\wedge$  are provided by equation (42). These recovered color data are provided via line 637.

### Examples

5

#### **Example 1**

##### **(Bayer Pattern With Three Colors)**

The present invention is applicable to two-dimensional array of image sensing elements, wherein the elements are arranged in a so-called "Bayer Pattern." The disposition of colors in a preferred variant of such pattern is shown in the following diagram:

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197

At R pixels:  $G^{\wedge} = R - (R-G)_{mf\_row}$

At G pixels:  $R^{\wedge} = G + (R-G)_{mf\_row}$

The same basic steps are employed at even numbered rows, but using the colors G and B. After treatment of both the odd- and even-numbered rows, this results in the following information:

5

|               |               |               |               |               |               |     |
|---------------|---------------|---------------|---------------|---------------|---------------|-----|
| $RG^{\wedge}$ | $R^{\wedge}G$ | $RG^{\wedge}$ | $R^{\wedge}G$ | $RG^{\wedge}$ | $R^{\wedge}G$ | ... |
| $GB^{\wedge}$ | $G^{\wedge}B$ | $GB^{\wedge}$ | $G^{\wedge}B$ | $GB^{\wedge}$ | $G^{\wedge}B$ | ... |
| $RG^{\wedge}$ | $R^{\wedge}G$ | $RG^{\wedge}$ | $R^{\wedge}G$ | $RG^{\wedge}$ | $R^{\wedge}G$ | ... |
| $GB^{\wedge}$ | $G^{\wedge}B$ | $GB^{\wedge}$ | $G^{\wedge}B$ | $GB^{\wedge}$ | $G^{\wedge}B$ | ... |

...etc.

The odd numbered rows are now missing only an estimate for the blue intensity at each element, and even numbered rows are missing only an estimate of the red intensities. Values for green have already been either measured or estimated at every element, so the recovery of green intensities is complete at this point.

In Step 2, the still-missing colors are recovered by applying the color recovery methodology mentioned in Step 1, but in a column-wise fashion.

Recovery begins with a one-dimensional interpolation of the R and B values in the column direction.

15 For the odd-numbered columns, two color differences, (R-B) and (R-G), are formed. These are filtered in the column direction with a 1-D median filter, and the missing colors are recovered as follows:

At  $RG^{\wedge}$  elements:  $B^{\wedge} = R - (R-B)_{mf\_col}$

At  $B^{\wedge}G$  elements:  $R^{\wedge} = G + (R-G)_{mf\_col}$

Even-numbered columns are treated similarly, except the required color differences are now (R-B) and (B-G). The missing colors are recovered according to:

$$\text{At } R^{\wedge}G \text{ elements: } B^{\wedge} = G + (B-G)_{mf\_col}$$

$$\text{At } G^{\wedge}B \text{ elements: } R^{\wedge} = B + (R-B)_{mf\_col}$$

At this point, all colors have been recovered and the process is complete.

Note that in all of the recovery operations, the recovered color at each element is computed as the combination of the one explicitly measured color with a filtered color difference.

### Example 2

#### (Bayer-like Pattern with Four Colors)

The method described in Example 1 is not restricted to a specific choice of colors, or to a specific disposition of colors. The following example illustrates this by application to a Bayer-like pattern in which there are two different shades of green (G1 and G2). This could happen by design, but in fact it is also likely to happen in practice even when a sensor is designed with only a single intended shade of green.

An inspection of the Bayer pattern shows that there are two types of G sites. The first G site (G1) has R sensors located above and below, and B sensors located to the right and left. The second G site (G2) has the B sensors located above and below, and the R sensors located to the right and left. Unless manufacturing methods are ideal, these two sites are likely to exhibit slightly different responses, and such differences may result in color fidelity problems. Even in the absence of manufacturing differences, the difference in structure of the sensing elements in the horizontal and vertical directions may lead to response differences due to electrical or optical “cross-talk” between pixels. Therefore, instead of treating these sites as equivalent, superior results are obtained by treating them as effectively different shades of green. The color layout is then:

R G1 R G1 R G1 R G1 R G1 ...

G2    B   G2    B   G2    B   G2    B   G2    B   ...  
 R   G1   R   G1   R   G1   R   G1   R   G1   ...  
 G2    B   G2    B   G2    B   G2    B   G2    B   ...  
 ...etc.

In Step 1 of the recovery, each row is digitally processed to recover any colors that exist in that row, particularly by applying the methodologies described in U.S. Pat. No. 4,774,565 (W.T. Freeman) for a one-dimensional array. The result is:

R,G1<sup>^</sup>   R<sup>^</sup>,G1   R,G1<sup>^</sup>   R<sup>^</sup>,G1   R,G1<sup>^</sup>   R<sup>^</sup>,G1   ...  
 G2,B<sup>^</sup>   G2<sup>^</sup>,B   G2,B<sup>^</sup>   G2<sup>^</sup>,B   G2,B<sup>^</sup>   G2<sup>^</sup>,B   ...  
 R,G1<sup>^</sup>   R<sup>^</sup>,G1   R,G1<sup>^</sup>   R<sup>^</sup>,G1   R,G1<sup>^</sup>   R<sup>^</sup>,G1   ...  
 G2,B<sup>^</sup>   G2<sup>^</sup>,B   G2,B<sup>^</sup>   G2<sup>^</sup>,B   G2,B<sup>^</sup>   G2<sup>^</sup>,B   ...  
 ...etc.

In step 2, there are now two missing values per element. In the odd-numbered columns, for example, the R,G1<sup>^</sup> sites are missing values for G2 and B, while the G2,B<sup>^</sup> sites are missing values for R and G1. To remedy this, all four color-values are interpolated in the column-wise direction, and the required color differences (R-G2), (R-B), and (G1-G2) are formed. Then the missing values are estimated as:

$$\begin{aligned}
 \text{At R,G1}^{\wedge} \text{ sites:} \quad & G2^{\wedge} = R - (R-G2)_{mf\_col} \\
 & B^{\wedge} = R - (R-B)_{mf\_col} \\
 \text{At G2,B}^{\wedge} \text{ sites:} \quad & G1^{\wedge} = G2 + (G1-G2)_{mf\_col} \\
 & R^{\wedge} = G2 + (R-G2)_{mf\_col}
 \end{aligned}$$

A similar pattern is followed for even-numbered columns, but using color differences (G1-G2), (B-G1) and (R-B).

The procedure just described produces results with fidelity equivalent or superior to that of the two-dimensional form of color recovery described in U.S. Pat. No. 4,774,565 (W.T. Freeman), and the computations are considerably faster and simpler to implement in special-purpose hardware.

5

### Example 3

Examples 1 and 2 above refer to rows and columns of pixels, indicative of a rectangular array of sensing elements. It will be appreciated, however, that it is not a requirement of the present invention that the rows and columns be disposed at right angles to one another. For example, the present invention can be performed on a hexagonal array of pixels as shown in FIG. 8, using "rows" and "columns" 10 and 12 that are separated in angle by 60 degrees. Thus, the step of recovering missing color information along a first dimension according to the invention is conducted, for example, along dimension of 10 of the hexagonal array, and the step of recovering missing color information along a second dimension is conducted along dimension 12. The conduct of both is substantively equivalent to those identified in Example 1. Likewise, the results should also be substantively equivalent.

While the invention has been described with reference to particular embodiments, it will be understood that the present invention is not limited to the particular constructions and methods herein disclosed and/or shown in the drawings, but also comprises any modifications or equivalents within the scope of the claims.